



ACDC-1000A Digital AC/DC Clamp-on Multimeter



- AC/DC Volts to 600
- AC/DC Amps to 1000
- Ohms to 1999
- In-rush Current capture (80 mS response)
- Low Battery & Over-range indicators
- Withstands momentary overloads up to 50%
- Large, easy to read display



FEATURES	RANGE & RESOLUTION*	ACCURACY
AC/DC Voltage	0-199.9, 600 V	± 1% Rdg + 1 LSD @ 0-600V DC** ± 1% Rdg + 5 LSD @ 0-600V AC**
AC/DC Current	0-199.9, 1000 A	± 1% Rdg + 5 LSD @ 0-999A DC, 0-750A AC**
Resistance	0-199.9, 1999 Ω	± 1% Rdg + 1 LSD

OPTIONAL ACCESSORIES	PART NUMBER
Line Splitter (Energizer)	A47L
Amptran 50-1 Current Transformer, 5000 Amps Max, AC ONLY	CT50-1
Amptran 50-1 Current Transformer, 3000 Amps Max, AC ONLY	CT50-2

REPLACEMENT PARTS <i>(supplied with product)</i>	PART NUMBER
Test Leads	DTL-1A
Ohmmeter attachment	OHB-4HE
Alligator clip adaptors for DTL-1A test leads	VRC-320
Replacement screw in probe tips for DTL-1A Test leads	VPT
Fuse, 1 Amp/600 Volt Fast Blow	8AG-360x023
Instruction Manual	www.AMPROBE.com

*We use a special notation to indicate range AND resolution using a single number. For example: number 40.00 indicates range of 40 and resolution 0.01 (two digits after the point with the 1 as an increment, unless otherwise specified).
**For other ranges see website (<http://www.AMPROBE.com>)